



**Note: This API call is for DOS and Win16 personality only. Use [Family API](#) for portability.**

2018/09/07 05:04 · prokushev · [0 Comments](#)

# AH=00H

## Version

2 and higher

## Brief

Obtains the version number of the Extended Memory Specification that is supported by the installed driver.

## Family API

none

## Input

```
AH = 00h
```

## Return

- AX status: 0000H = successful, 0001H = error and BL=XMS error code (if BL >= 80H) else = XMS version number in BCD; e.g., 0234H=2.34
- BX driver internal version number
- DX HMA flag: 0001H = HMA▲ exists; 0000H=HMA does not exist

## Notes

## See also

From:

<http://ftp.osfree.org/doku/> - **osFree wiki**

Permanent link:

<http://ftp.osfree.org/doku/doku.php?id=en:docs:xms:api:00&rev=1703056090>

Last update: **2023/12/20 07:08**

